

Add Port Campus Printer to Personal Computer

1 Download Driver

In a search engine, search for
or visit

🔍 c3502 ricoh driver 🗣️

https://support.rioh.com/bb/html/dr_ut_e/re2/model/mpc300/mpc300.htm

Install the driver to your computer.



2 Add the Printer


Open **System Settings** from your dock  or **Applications Folder**.

Scroll down the list, and select

 **Printers & Scanners**


But first! Make sure you are connected to the internet before proceeding to next steps.
If using WIFI, only connect to **eduroam** for printing!

3 Click **Add Printer, Scanner or Fax.**




Select **port campus ricoh mp c3502** from the list. You may also do a search for **c3502** at the top to narrow down the list.


If you'd like, you can rename the printer to something else, such as **Port Campus Printer**



4 Click **Select Software** from the **Use** pulldown.




Select **RICOH Aficio MP C3502 PS** from the list, click **OK**.




You may also type **C3502** in search field to shorten the list

5

Click **Add**



Click **OK** once setup is complete.




6

Create **Black & White Preset**

Open a document in an application such as **Pages**.


Go to **File>Print**
Scroll down to **Printer Options**

Click on **Printer Features**




Printer Features

Set Color Mode to **Black and White**, press **OK**.



7

It's now time to save these settings as a **Print Preset**
 Scroll to the top, and select **Save Current Settings as Preset....**



Name the preset **Black & White**,
 click **OK**.

Preset Name:

Available For: ☒ Port Campus Printer
☐ All printers



Type: ☐ Custom Preset
☒ Print Job Preset



8

Print

To print, go to **File>Print** in your software.

****At Port Campus you must always see the
 Print Dialogue window, where you will see the
 Printer and the Preset. ****

Printer  Port Campus Printer (2nd Floor Building Operations) 

Presets  Black & White 


Some software will bypass this Print Dialogue screen.
 You may need to press a **Setup** or **Printer** button to
 access the **Print Dialogue** screen.

Enter your **NSCAD user credentials**,
 without @nscad.ca, and click **OK**.

**Authentication Error means there is an error
 in the credentials.**

**Connection Refused means you are using
 the wrong internet connection or no internet
 connection.**

**** Always print using ethernet or eduroam wifi.**

 Enter your name and password for the printer "Port Campus Ricoh".

Name:

Password:

☐ Remember this password in my keychain